



DEVICE CHARGING:

For the first time of use, please fully charge the unit for at least 2~3 hours

Using the USB charger or using docking station to charge

- Place the device on the docking station.
- Connect the Micro USB side of the cable to the docking station port and connect the other end of the cable to the designated AC power source (USB/AC adaptor).

SWITCHING THE DEVICE ON AND OFF:

- **To turn on the device:** press the side power button for 1 second, all the LEDs will flash rapidly. Device can be also turned on automatically by charging via USB or put it into the docking station.
- **To turn off the device:** press and hold the side button and SOS button together for 1 second until the LEDs off.

WATERPROOF:

Your SkyAngel 911FD is 100% waterproof and can be worn in the shower or even submerged under water for brief periods of time. Do not submerge for long periods of time.

PLEASE NOTE: Do not remove the back cover at any time; this will break the waterproof seal. Also, removing the back cover voids any and all warranties.

LOCATING:

To receive a text message with a GoogleMaps link to the current location of the device send a text to the phone number associated with the device. The body of the text should be 'LOC'.

WHAT DO THE FLASHING LIGHTS ON THE SIDE OF THE UNIT MEAN?

Charging Status – Blue Light:

- Blue light is on solid: the unit is charging
- Blue light is blinking quickly: unit has less than 15% power and should be recharged
- Blue light is off / blinking slowly: unit is fully charged

CELL SIGNAL Status – Green Light:

- Green single flash every 3 seconds: unit is connected to Cellular network

PROGRAMMING THE UNIT:

The unit has 2 buttons that will dial: the SOS button on the top and the On/Off/Call button on the side.

The unit can store 3 contact numbers. Contacts 1, 2 and 3 can be dialed when you press the SOS button.

Contacts 2 and 3 are can be dialed alternately by pressing the On/Off/Call button.

To program the contact numbers send a text message to the phone number assigned to your unit.

To program the first contact send a text message exactly as follows: 'a1,PHONE NUMBER TO CALL'

To program the second contact send a text message exactly as follows: 'b1,PHONE NUMBER TO CALL'

To program the third contact send a text message exactly as follows: 'c1,PHONE NUMBER TO CALL'

Example, to program the first contact number as 1234567890, send the following text message to the phone number assigned to the device 'a1,1234567890'

ACTIVATING AN SOS ALARM:

Press and hold the SOS button for 3 seconds until the device vibrates, and then the green light will start to flash rapidly to confirm the request. After that, the unit will text and then call your 3 contact numbers in order.

--OR --

Press the On/Off/Call button on the side for 3 seconds until the unit vibrates, and then green light will start to flash to confirm the request. After that, the unit will call the second and third contact numbers in order.

To end the call, press the SOS button.

LOW BATTERY ALARM:

The SkyAngel 911FD has a Low Battery Alarm. When the battery on the unit gets to less than 15%, the blue light on the unit will flash rapidly to warn the user that the unit needs to be charged.

For questions or technical assistance, please contact our office:

Assistive Technology Services - (615) 562-0043 - Questions@ATS-TN.com

NOTE: Our hours of operation are Monday – Friday, 8:00 AM – 6:00 PM Central Time